




<http://atx-led.com>


Low Voltage
Ceiling Box – 4 inch

UL Listed
E511129


Mounting for:
WiFi Access Points
Smoke Detectors
Cameras



Longer tabs for faster installation on Truss ceilings



Product Description - Ceiling Mount Box



This device solves 3 requirements for Code Compliant installation of Low Voltage devices in ceilings

- a) All wires inside Junction boxes
- b) Mechanical support by the rafters not the sheetrock
- c) Fire rated UL94V-0 polycarbonate material

It also solves problems in other ways

- a) Built in depth guide eliminates pre-installation depth measurement
- b) Allows hole cutting, tape, float, paint to be done by the sheetrock team before installing the lights
- c) Allows super fast trim installation
- d) Positions low voltage wire above sheetrock to avoid damage
- e) Marks the source and destination of the wires








UL Listed


UL 2269 listed with file E511129 as a stand alone 'Signaling Cable Outlet Box'. It is also listed under File E522252 as an accessory to the DL-120 LED fixture, and under ETL E5004252 as an accessory to the P023R6 LED fixture family.

Dimensions

2 ¼ inch deep, 4 inches diameter, suitable for truss spacing of 14 to 24 inches. Holes are provided for accessories at standard 4-0 box spacing for 8-32 screws.. V-Springs protrude to the back to a total depth of 3 ¾ inches from the face off the Sheetrock

Mounting Options

AL-CBOX4-N		<p>Nailer – use #10 8d 2 ¼ inch nails</p> <p>Can attach the Hanger Bar shown Below</p>
AL-CBOX4-HB	 <div data-bbox="532 898 1105 1201">  <p>AL-CBOX4 Ceiling Box with Hanger Bar for Low Voltage Devices</p>  <p>ATX LED, Inc. www.atxled.com Made in China</p> <p>50 Pack 24 x 16 x 9 in 34 lbs</p> <ul style="list-style-type: none"> ➤ See ATX LED website for compatible devices ➤ UL-listed low-voltage junction box E511129 ➤ 14.3 inch to 22.5 inch adjustable hanger bar ➤ Suitable for truss or joist installations ➤ Not intended for ceiling fans ➤ Use 2-inch 8-32 screws for pendants ➤ See also AL-CBOX-N for installations with 8d nails </div>	<p>No Nailer option</p> <p>Hanger Bar included</p> <p>Pre-assembled</p>
AL-HB available separately	 <p>U attach device, 2 screws included</p> <div data-bbox="477 1707 1146 1866">  <p>Hanger Bar</p>  <p>ATX LED, Inc. www.atxled.com Made in China</p> <p>50 Pack 21 x 15 x 4 in 27.5 lbs</p> <ul style="list-style-type: none"> ➤ Hanger bar only ➤ Ideal with AL-CBOX4 or AL-MBOX4 ➤ See ATX LED website for compatible products ➤ Suitable for truss or joist installations ➤ Not intended for ceiling fans </div>	<p>Includes U attachment and 2 screws to attach to CBOX4-N or other boxes</p>



Truss Installation





Beam installation

Compatible Fixtures

Model	type	Note
AL-WS-R@R	Work light	Temporary Lighting
DL-120	Downlight for tall ceilings	Brightest downlight, spot source
DL-125	Gimbal downlight	Can be adjusted for angle
P023R6	Puck Downlight	Best for low ceilings
P023R6-M	Puck Downlight	Motion sensing
P023R6-48v	Puck Downlight	For On/Off switch projects


P023R6-S and P023R6-F are not compatible

Wiring Examples



Ready@Rough Work Lights

Because the ATX LED family operates at low voltage – you can provide light in your projects at Rough – and not wait until trim. Our R@R family of products provides light immediately, which is replaced by the final project lighting at trim.



Carton of 50

ATX
LED

AL-CBOX4

Ceiling Box with Hanger Bar for Low Voltage Devices



DL-120 LED
(not included)



- See ATX LED website for compatible devices
- UL-listed low-voltage junction box E511129
- 14.3 inch to 22.5 inch adjustable hanger bar
- Suitable for truss or joist installations
- Not intended for ceiling fans
- Use 2-inch 8-32 screws for pendants
- See also AL-CBOX-N for installations with 8d nails

ATX LED, Inc.
www.atxled.com
Made in China

50 Pack

24 x 16 x 9 in
34 lbs